



**NB - A fault involving the Gas valve circuit will occur even if there is no heating demand. Reset appliance when there is no heat demand to identify a fault of this nature. Once corrected, there is no need to use the reset button, as the fault will self clear.**

**NB - A fault involving the high limit circuit will occur even if there is no heating demand. Reset appliance when there is no heat demand to identify a fault of this nature. Once corrected, the reset button will need to be pushed, as this fault will not self clear.**

**NB - A fault in the ionisation circuit will be identifiable when the ignition cycle is repeated 5 times.**

**NB - A fault involving the fan circuit or ignition circuit can only occur if there is a heat demand. Once corrected, the reset button will need to be pushed, as this fault will not self clear.**